

pecification

chnical

# **CO-AF Carbon Monoxide Sensor**




### Figure 1 CO-AF Schematic Diagram

**PERFORMANCE** Sensitivity

**PATENTED** 

55 to 90



nA/ppm in 400ppm CO

	Response time Zero current Resolution Range Linearity Overgas limit	t <sub>90</sub> (s) from zero to 400ppm CO ppm equivalent in zero air RMS noise (ppm equivalent) ppm CO limit of performance warranty ppm error at full scale, linear at zero, 1000ppm CO maximum ppm for stable response to gas pulse		< 25 -4 to +2 < 0.5 5,000 +15 to +25 10,000
LIFETIME	Zero drift Sensitivity drift Operating life	ppm equivalent change/year in lab air % change/year in lab air, monthly test months until 80% original signal (24 month warranted)		< 0.2 < 8 > 24
ENVIRONMENTA	•	C % (output @ -20°C/output @ 20°C) @ 400ppm CO % (output @ 50°C/output @ 20°C) @ 400ppm CO ppm equivalent change from 20°C ppm equivalent change from 20°C		63 to 88 102 to 115 < ± 3 < ± 8
CROSS SENSITIVITY	Filter capacity Filter capacity Filter capacity Filter capacity Filter capacity H <sub>2</sub> S sensitivity NO <sub>2</sub> sensitivity NO sensitivity NO sensitivity SO <sub>2</sub> sensitivity H <sub>2</sub> sensitivity H <sub>2</sub> sensitivity C <sub>2</sub> H <sub>4</sub> sensitivity NH <sub>3</sub> sensitivity	ppm-hours ppm-hours ppm-hours ppm-hours % measured gas @ 20ppm % measured gas @ 10ppm % measured gas @ 50ppm % measured gas @ 20ppm % measured gas @ 20ppm % measured gas @ 400ppm % measured gas @ 400ppm % measured gas @ 20ppm % measured gas @ 20ppm	$\begin{array}{c} {\rm H_2S} \\ {\rm NO_2} \\ {\rm NO} \\ {\rm SO_2} \\ {\rm H_2S} \\ {\rm NO_2} \\ {\rm CI_2} \\ {\rm NO} \\ {\rm SO_2} \\ {\rm H_2} \\ {\rm at} \ 20^{\rm o}{\rm C} \\ {\rm C_2H_4} \\ {\rm NH_3} \end{array}$	250,000 600,000 20,000 300,000 < 0.1 < 0.1 < 5 < 0.1 < 60 < 25 < 0.1
KEY SPECIFICATIONS	Temperature range Pressure range Humidity range	°C kPa % rh continuous		-30 to 50 80 to 120 15 to 90



At the end of the product's life, do not dispose of any electronic sensor, component or instrument in the domestic waste, but contact the instrument manufacturer, Alphasense or its distributor for disposal instructions.

 $\Omega$  (recommended)

months @ 3 to 20°C (stored in sealed pot)

## **Apollosense Ltd**

6

< 6

10 to 47

Shenzhen:

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

Storage period

Load resistor

Weight

T-I · /

Tel: (86-755) 83680810 83680820 83680830 83680860 Fax: (86-755) 83680866 Hong Kong:

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903

Fax: (852) 2737 0938

Email: sales@apollounion.com





Specification

echnica

# **CO-AF Performance Data**

### Figure 2 Sensitivity Temperature Dependence




Figure 2 shows the variation in sensitivity caused by changes in temperature.

This data is taken from a typical batch of sensors. The mean and ±95% confidence intervals are shown.

### Figure 3 Zero Temperature Dependence




Figure 3 shows the variation in zero output caused by changes in temperature, expressed as ppm gas equivalent, referenced to zero at 20°C.

This data is taken from a typical batch of sensors.

### Figure 4 Response to Exposure to 2% CO




Figure 4 shows the excellent response to step changes in CO concentrations from zero to 2% CO by volume.

This data is taken from a typical batch of sensors.

## Apollosense Ltd

Shenzhen:

Fax: (86-755) 83680866

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

Tel: (86-755) 83680810 83680820 83680830 83680860

Hong Kong:

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903 Fax: (852) 2737 0938 Email: sales@apollounion.com